

Hearing Helper™ FM Tour Guide System • Model TGS PRO 720



Description:


The Hearing Helper™ FM Tour Guide System, model TGS PRO 720, helps tour group members with hearing difficulties overcome background noise and distance from the guide. Use it in factories, museums, power plants—anywhere hearing assistance is needed. System includes one (1) T36 transmitter with MIC 096 microphone, ten (10) R35 receivers, batteries and system carry case. System operates on 72-76 MHz bandwidth for hearing assistance.

Provides hearing assistance for:

- Group Tours • Destination Marketing Organizations • Cruise Ships • Tourism Offices
- University Tours • Large-Scale Guided Attractions • Museum & Presentation Centers
- Chambers of Commerce • Factory/Plant Tours

PPA T36 FM Transmitter

Dimensions:	4.1" L x 2.8" W x 1.1" H (104 mm x 71 mm x 28 mm)
Weight:	2.6 oz (74 g), no batteries
Color:	Black, shatter-resistant PC/ABS plastic
Battery Type:	Two (2) AA 1.5 V non-rechargeable Alkaline batteries (BAT 001), 70 mA nominal current drain, 30 hours approx. life or Two (2) AA 1.5 V NiMH rechargeable batteries (BAT 026), 70 mA nominal current drain, 20 hours per charge approx., recharges in 14–16 hours, uses CHG 3502 or CHG 3512 Charger
Operating Freq's:	Selectable, 16 channels, 72.1 – 75.9 MHz* (channels 1-8 correspond with R35-8 receiver channels)
Stability:	± .005%, frequency synthesized, crystal reference, PLL
Modulation:	Wide-band FM, 75 kHz pk, 75 µS pre-emphasis
RF Output:	80 mV/m at 3 m (max. allowed by FCC rules)
Freq Response:	200 Hz to 13 kHz, ± 3 dB at 1% max. THD
Signal-to-Noise Ratio:	65 dB (typical) transmitted
Transmit Antenna:	Integral with microphone cord
Microphone:	Electret type, 3.5 mm mono phone plug
External Controls:	Momentary push button: push and hold 3 seconds for power On/Off, push and release for microphone mute On/Off; Rotary sixteen channel switch (with internal channel lock switch)
Mic Input:	3.5 mm mono phone jack with electret mic bias, internal adjustable gain with 25 dB range
Aux Input:	2.5 mm stereo phone jack, internal adjustable gain with 60 dB range
Audio Compression:	1:1 or 2:1 ratio selected with internal slide switch
Compatible Receivers:	PFM R31, PFM R32, PFM R33, PFM R36, PPA R35, PPA R35-8, PPA R1600
Approvals/Directives:	FCC, Industry Canada, RoHS, WEEE
Warranty:	5 years, parts and labor (90 days on accessories)
Note:	FCC regulations, section 15.21, requires the user to comply with the rules of transmitter operation. Any changes or modifications made by the user not expressly approved for compliance may result in the loss of all privileges and authority to operate the equipment



T36 Top



T36 Front

*DISCLAIMER: FCC RULES LIMIT USE OF THIS EQUIPMENT TO AUDITORY ASSISTANCE


NOTE: SPECIFICATIONS SUBJECT TO CHANGE WITHOUT NOTICE!

Hearing Helper™ FM Tour Guide System • Model TGS PRO 720



PPA R35 Receiver

Dimensions:	4.1" L x 2.85" W x 1.2" H (104.1 mm x 72.4 mm x 30.4 mm)
Weight:	4.5 oz (127 g)
Color:	Black
Battery Type:	Two (2) AA non-rechargeable alkaline batteries (BAT 001), approx. 100 hours battery life (OR) Two (2) AA rechargeable NiMH batteries (BAT 026), 1400 mA, approx 56 hours battery life
Current Consumption:	Nominal 40 mA
Operating Freq.:	Pre-tuned, adjustable, 72 MHz-76 MHz *
Intermediate Freq.:	75 kHz
FM Deviation:	75 kHz
De-Emphasis:	75 μ S
AFC Range:	\pm 120 kHz
Sensitivity:	2 μ V at 12 dB Sinad with squelch defeated
Input Overload:	20 mV
Frequency Response:	100 – 15 kHz, \pm 3 dB
Signal-to-Noise Ratio:	65 dB at 10 μ V
LED Power Indicator:	Power: Green; Low Battery: Red
Receive Antenna:	Integral with earphone/headphone cord
Audio Output:	35 mW, max. at 16 Ω
Output Connector:	3.5 mm mono phone jack
Approvals:	FCC, Industry Canada, RoHS, WEEE
Notes:	The R35 Receiver can be field tuned to any of 10 wideband channels using the PLT 005 Tuning Tool.
Warranty:	5 years, parts and labor (90 days on accessories)



R35 Top



R35 Front

*DISCLAIMER: FCC RULES LIMIT USE OF THIS EQUIPMENT TO AUDITORY ASSISTANCE.

NOTE: SPECIFICATIONS SUBJECT TO CHANGE WITHOUT NOTICE!