



# RF-DC-24

24 Bay Charging Case for  
RF-RX1 Receivers and RF-TX1 Transmitters



CONTACTA RADIO FREQUENCY

The RF-DC-24 Charging Case is for use with the RF-RX1-915 Portable Receiver and RF-TX1-915 Portable Transmitter. It can hold up to 24 devices in a standing position with a simple drop-in connection.

The built-in digital panel enables fast and easy programming of multiple devices, including data copy and channel sync. The smart programming software provides fast setup from a master device.

### Physical Data

Dimensions	Height - 6.6" Width - 17.2" Depth - 10.4"
Weight	10.3lbs
Finish	Mixed (Silver/Black)
Construction	High grade metallic protective case with inner padding

### Technical Data

Charging Bays	24
Charging Current	350 ± 50 mA, per bay
Charging Time	4~6 hours with 2100 mAh NiMH rechargeable batteries
Charging Algorithm	PWM control, -/ Δ V and Timer power-off detector
Power Requirements	AC 100~240V switching power adapter (50/60Hz), DC 12V, 5A
Ambient Temperature	0C-40C (32F-104F)



### Applications

**This wireless assistive listening system can be used in venues, such as:**

- › Museums
- › Places of Worship
- › Auditoriums
- › Exhibitions/Events/Conferences
- › Any space where guided tours take place

### Includes

- › Power Supply
- › USB Drive with PC Programming Software

contacta

Phone: (616) 392-3400  
Email: sales@contactainc.com  
www.contactainc.com