



RF-TX1-EM

Ear-Worn Microphone for use with the RF-TX1-915 Portable Transmitter



CONTACTA RADIO FREQUENCY

The RF-TX1-EM ear-worn microphone is compatible with the RF-TX1-915 Portable Transmitter. It fits around the back of the ear with the microphone placed close to the mouth. It's specifically designed for versatility and portability without distracting your audience. The microphone has a 3.93ft cable, mini-XLR connector and comes with a garmet clip. It enables hands free communication using a high quality condenser microphone capsule.

Physical Data

Dimensions	Microphone Height - 2.30" Width - 6.20" Depth - 1.25" Cable length - 47.2" / 3.93 feet
Weight	0.04lbs

Technical Data

Connector	Mini-XLR
Power Supply	1 ~ 10V/DC phantom voltage
Transducer Type	Condenser capsule
Polar Pattern	Unidirectional
Sensitivity	-47 ±3dB @f=1 kHz, S.P.L=1Pa, 0dB=1V/Pa -67 ±3 (0dB = 1V/microbar)
Frequency Response	70Hz - 16kHz



Applications

This wireless assistive listening system can be used in venues, such as:

- › Museums
- › Historical Sites
- › Exhibitions/Events/Conferences
- › Any space where guided tours take place

Compatible Accessories

- › RF-TX1-915, Portable Transmitter

contacta

Phone: (616) 392-3400
Email: sales@contactainc.com
www.contactainc.com