



RF-TX1-LM

Lapel Microphone for use with the RF-TX1-915 Portable Transmitter



CONTACTA RADIO FREQUENCY

The RF-TX1-LM lapel microphone is compatible with the RF-TX1-915 Portable Transmitter. The microphone has a 3.28ft cable, mini-XLR connector and comes with a tie clip. It enables hands free communication for clear sound using a high quality condenser microphone capsule.

Physical Data

Dimensions	Microphone Height - 0.44" Width - 0.44" Depth - 0.97" without clip
	Tie Clip Height - 0.25" Width - 1.74"
	Cable length - 39.30" / 3.28'
Weight	0.05lbs with clip

Technical Data

Connector	Mini-XLR
Power Supply	1~5V/DC phantom voltage
Transducer Type	Condenser capsule
Polar Pattern	Unidirectional
Sensitivity	-50 ±3dB @f=1 kHz, S.P.L=1Pa, 0dB=1V/Pa
Frequency Response	180 Hz ~ 17 kHz



Applications

This wireless assistive listening system can be used in venues, such as:

- › Museums
- › Historical Sites
- › Exhibitions/Events/Conferences
- › Any space where guided tours take place

Compatible Accessories

- › RF-TX1-915, Portable Transmitter

contacta

Phone: (616) 392-3400

Email: sales@contactainc.com

www.contactainc.com